

# shop drawing

project specification

fixture type                    D632\_\_ - \_\_L - \_\_\_\_Watts - OAL\_\_\_\_" - \_\_\_\_Watts per foot

**Example:**D632b - 3 - 24" - 13 - 120

Fixture nbr    lamps    overall length    watts            volts

## Lighting specifications:

### D632 straight - biax

#### 13w:

D632 3-13w oal 24"	3 x 13w lamps	8" o.c.
D632 4-13w oal 36"	4 x 13w lamps	9" o.c.

#### 18w:

D632 2-18w oal 24"	2 x 18w lamps	12" o.c.
D632 4-18w oal 48"	4 x 18w lamps	12" o.c.

#### 36w:

D632 2-36w oal 36"	2 x 36w lamps	18" o.c.
D632 4-36w oal 72"	4 x 36w lamps	18" o.c.

#### 40w:

D632 2-40w oal 48"	2 x 40w lamps	24" o.c.
D632 4-40w oal 96"	4 x 40w lamps	24" o.c.

#### 50w:

D632 50w oal 24"	1 x 50w lamp	24"
D632-2 50w oal 48"	2 x 50w lamps	24" o.c.

Job Name:

Job Nbr:

Tag:

Distributor:

Electrician

Engineer:

Interior Design:

Architect:

note: site measurements required

Note:

Any Changes or modifications to mmj lighting 96 ltd lighting fixtures, must be done in the mmj lighting 96 ltd factory. Any modifications or changes done in the field will void all warranties and approvals.

multiple lamp integral electronic ballast. type 1 outdoor minimum operating temperature -20 deg F [ 30 deg C ] BALLAST WARRANTY 5 YEARS FROM DATE OF PURCHASE

Finishes:

white, black, natural, polished\_\_\_\_\_

End caps included.

Specify power feed    left or    right

Shop drawing D632 1.20.04



### D632b multi lamp – bendable biax:

#### 13w:

D632b 3-13w oal 24"	3 x 13w lamps	8" o.c.
D632b 4-13w oal 36"	4 x 13w lamps	9" o.c.

#### 18w:

D632b-2-18w oal 24"	2 x 18w lamps	12" o.c.
D632b-4-18w oal 48"	4 x 18w lamps	12" o.c.

#### 36w:

D632b-2-36w oal 36"	2 x 36w lamps	36" o.c.
D632b-4-36w oal 72"	4 x 36w lamps	18" o.c.

#### 40w:

D632b-2-40w oal 48"	2 x 40w lamps	24" o.c.
D632b-4-40w oal 96"	4 x 40w lamps	24" o.c.

#### 55w:

D632b-2-50w oal 48"	2x 50w lamps	48" o.c.
---------------------	--------------	----------

### D632 multi lamp bendable - DIMMING BALLAST

D634b-2-32D oal

D632b-2-50D oal 48"	2 x 50w lamps	24" o.c.
---------------------	---------------	----------

**Quad:** 13w, 18w, 26w.

D632- \_\_L\_\_W, OAL\_\_\_\_" straight

D632b \_\_L\_\_W, OAL\_\_\_\_" bendable