

shop drawing

project specification

fixture type ETH ETB Extruded Aluminum housing with snap on cover and electronic ballast size as specified.

Job Name:
 Job Nbr:
 Tag:
 Distributor:
 Electrician:
 Engineer:
 Interior Design:
 Architect:
 note: site measurements required

Note:
 Any Changes or modifications to mmj lighting 96 ltd lighting fixtures, must be done in the mmj lighting 96 ltd factory. Any modifications or changes done in the field will void all warranties and approvals.

G – green to ground
 B – black 120v line
 W – white 120v neutral




Base – 2.0' x 2.0"

Y – Yellow connection one to each fixture

R – Red connection to 1st fixture
 R – Red connection to 2nd fixture
 R – Red connection to 3rd fixture
 R – Red connection to 4th fixture

ETB140 Plan view of enclosure and snap on cover [screws not required]



Enclosure complete with electronic ballast :

Note:

Enclosure dimensions:

2.0" x 2.0" square - length

ETH ETB28	28w	12"
ETH ETB35	35w	12"
ETH ETB64	64w	12"
ETH ETB70	70w	12"
ETH ETB128	128w	18"
ETH ETB140	140w	18"
ETH ETB220	220w	24"

ALL PRODUCTS ARE c CSA us APPROVED.



eth etb shop drawing revised 06.14.07

150 Ferrier Street, Unit 2, Markham, Ontario L3R 3K3
 T 905 479 0788 F 905 479 7117 E sales@mmjlighting96.com

www.mmjlighting96.com

mmj
 lighting 96 ltd